



## TS101-8 8 Watt Radio Transceiver

The TS101-8 is an 8 Watt digital FM radio transceiver that is specifically designed for voice and data paging applications. The unit contains a synthesized UHF or VHF transmitter with a highly sensitive receiver for channel monitoring and an integrated switching power supply to support the transceiver's stable operation.



- ***UHF or VHF Frequency Band***
- ***Digital and Analog Paging Formats***
- ***8 Watt Power Output***
- ***Synthesized Frequency***
- ***Highly Sensitive Receiver***
- ***Narrow Band Operation***

### Specifications:

<b>Dimensions:</b>	2.1" high x 10.5 wide x 7.2 deep	<b>Frequency Range:</b>	148-174Mhz, 400-470MHz
<b>Weight:</b>	6.45 lb.	<b>Channel Spacing:</b>	12.5 KHz - Narrow band
<b>Power input:</b>	90-240VAC 50/60Hz 40Watt	<b>Stability:</b>	± 2.5 ppm
<b>Operating Temperature:</b>	10° to 140°F	<b>Data format:</b>	Digital 512-2400 BPS
<b>Output Power:</b>	Up to 8 Watt		Analog - 100Hz - 3.6KHz
<b>Receiver Sensitivity:</b>	<110dBm	<b>Enclosure:</b>	Durable metal case with
<b>Selectivity:</b>	50dB		LED power indicator.
<b>Input/Output impedance:</b>	50 Ohm	<b>Limited Warranty</b>	One-year Parts and Labor
<b>Modulation:</b>	FM		